

In the claims:

1. (Currently amended) A planar antenna array in a radar sensor for detecting objects in the vicinity of a motor vehicle, with a multitude of microstrip feeder lines (18) and a multitude of coupling slots (20) for emitting microwave energy into open space, characterized in that
 - the feeder lines (18) and the coupling slots (20) are embodied in a multilayer ceramic substrate (10) produced by means of the LTCC Low Temperature Co-fired Ceramic thick layer technique with an upper (12) and a lower grounded layer, and
 - the feeder lines (18) and coupling slots (20) are enclosed by plated-through contacts (14) from the upper grounded layer to the lower one, and
 - the feeder lines and coupling slots are surrounded at a fixed distance by plated-through contacts, the distance being smaller than a critical distance at which waveguide modes form.

Claim 2 cancelled.

3. (Currently amended) The antenna array according to claim 21, ~~characterized in that~~ wherein the fixed distance lies in the range from approx. $0.01 * \lambda$ to approx. $0.1 * \lambda$, where λ is the wavelength of the microwave radiation emitted.

4. (Currently amended) The antenna array according to claim 1, ~~characterized in that~~wherein each coupling slot (20) is enclosed by a single-row arrangement of plated-through contacts ~~(14, 30, 40, 42)~~.

5. (Currently amended) The antenna array according to claim 1, ~~characterized in that~~wherein each coupling slot (20) is enclosed by a double-row arrangement of plated-through contacts ~~(36, 38)~~, wherein the two rows are aligned with each other or offset from each other.

6. (Currently amended) The antenna array according to claim 1, ~~characterized in that~~wherein the distance of the coupling slots (20) from the end of the resonator is essentially $(2n-1) * \lambda/4$, where λ is the wavelength of the emitted microwave radiation and n is a natural number.

7. (Currently amended) The antenna array according to claim 1, ~~characterized in that~~wherein the distance of the coupling slots (20) from the back wall is essentially $2n * \lambda/4$, where λ is the wavelength of the microwave radiation emitted and n is a natural number.

8. (Currently amended) The antenna array according to claim 1, ~~characterized in that~~wherein the plated-through contacts ~~(30, 36, 38)~~ enclose the coupling slots (20) along an essentially rectangular

perimeter line, wherein the distance of the coupling slots (20) from the edge of the plated-through contacts (30, 36, 38) is preferably essentially $2n * \lambda/4$ perpendicular to the slot direction, where λ is the wavelength of the microwave radiation emitted and n is a natural number.

9. (Currently amended) The antenna array according to claim 1, ~~characterized in that~~ wherein the plated-through contacts (42, 46) enclose the coupling slots (20) along a perimeter line that bulges in the middle of the slots, wherein the distance is greater than $2n * \lambda/4$ in the middle of the slots and is less than $2n * \lambda/4$ outside the middle, where λ is the wavelength of the microwave radiation emitted and n is a natural number.

10. (Currently amended) The antenna array according to claim 1, ~~characterized in that~~ wherein the plated-through contacts (48, 50) enclose the coupling slots (20) along a perimeter line with rounded corners.

11. (Currently amended) The antenna array according to claim 1, ~~characterized in that~~ wherein two rows of plated-through contacts are provided spaced apart from each other by the distance of half a wavelength.

In the abstract of the disclosure:

In order to produce a planar antenna array in a radar sensor with a multitude of microstrip feeder lines (18) and a multitude of coupling slots (20) for emitting microwave energy into open space, which achieves a favorable antenna efficiency when embodied in a planar design using LTCC technology, the invention proposes embodying the feeder lines (18) and the coupling slots (20) in a multilayer ceramic substrate (10) produced by means of the LTCC thick layer technique with an upper and a lower grounded layer (12), as well as enclosing the feeder lines (18) and the coupling slots (20) with plated-through contacts (14) from the upper grounded layer to the lower one.